NAME

cdda2wav − dumps CD audio data into sound files with extra data verification

SYNOPSIS

cdda2wav [*options*][**dev=***device*] [*file(s)* or *directories*]

DESCRIPTION

cdda2wav can retrieve audio tracks from CDROM drives that are capable of reading audio data digitally to the host via SCSI (**CDDA**).

As **cdda2wav** implements strategies to work around typical defects on audio CDs it reads many disks that cannot be read by other software. As **cdda2wav** may be told to use **libparanoia** (see −**paranoia** option below) to verify the data that has been read from the medium, it delivers superior quality even if the medium is dusty, scratched or if other problems occur.

As **cdda2wav** may be directed to write the audio data to stdout, it writes all it's informational output to stderr by default. See **out**−**fd=***descriptor* option below.

Default settings

Cdda2wav defaults to reead the first audio track from the medium and the default verbose level is set to −**vtoc,summary,sectors,titles** and **cdda2wav** by default writes ∗**.inf** files. To extract all audio tracks with quality verification, it is recommended to call:

cdda2wav -vall cddb=0 -paranoia -B

Device naming

Most users do not need to care about device naming at all. If no **dev=** option was specified, **cdda2wav** implements **auto target** support and automagically finds the drive in case that exactly one CD-ROM type drive is available in the system. In case that more than one CD-ROM type drive exists on the system, a list of possible device name parameters may be retrieved with **cdda2wav** −**scanbus** or from the target example from the output of **cdda2wav dev=help**, then the **dev=** parameter may be set based on the device listing.

The *device* parameter to the **dev=** option explained below refers to *scsibus*/*target*/*lun* of the CD/DVD/BluRay-Recorder. If a file /etc/default/cdrecord exists, the parameter to the **dev=** option may also be a drive name label in said file (see FILES section).

OPTIONS

Informative options

−**h**

−**help** display version information for cdda2wav on standard output.

−**version**

display version and Copyright information.

Audio options

−**a** *divider*

−**divider** *divider*

sets rate to 44100Hz / *divider*. Possible values are listed with the −**R** option.

The default divider value is 1.

−**B**

−**bulk**

−**alltracks**

copies each track into a separate file.

The default is not to extract all tracks.

−**b** *bits*

−**bits−per−sample** *bits*
sets *bits* per sample per channel: **8**, **12** or **16**.

The default is 16 bits per sample.

−**c** *channels*

−**channels** *channels*
use:

1 for mono recording

2 for stereo recording

s for stereo recording with both channels swapped

The default is to do stereo recording.

−**C** *endianess*

−**cdrom−endianess** *endianess*
sets endianess of the input samples to 'little', 'big', 'machine' or 'guess' to override defaults. The value 'machine' or 'host' is evaluated as the actual byte order of the host CPU in the current OS.

The default is to detect cdrom endianess automatically.

−**cuefile**
Create a CDRWIN compatible CUE file. A CUE file that completely follows the CDRWIN documentation can only be used to create 1:1 copies if there is a single file with audio data for the whole disk. The ∗.inf file format implements more audio CD features than the CDRWIN CUE format and it allows to create 1:1 copies if there is one audio data file per track. Use the CUE file format for meta data only if you really need this format.

To allow **cdda2wav** to create CUE files, you must also specify −**t all** to switch **cdda2wav** into a mode that creates a single audio data file for the whole CD.

−**T**

−**deemphasize**
undo the effect of pre-emphasis in the input samples.

The default is to keep the audio data in the same state as on the medium and to mark the pre-emphasis state in the ∗**.inf** files.

−**L** *cddb mode*

−**cddb** *cddb mode*
does a cddbp album- and track title lookup based on the cddb id. The parameter cddb mode defines how multiple entries shall be handled.

Parameter	Description
-1	disable cddb queries. This is the default.
0	interactive mode. The user selects the entry to use.
1	first fit mode. The first entry is taken unconditionally.

cddbp−server=*servername*
sets the server to be contacted for title lookups.

cddbp−port=*portnumber*
sets the port number to be used for title lookups.

−**d** *duration*

−**duration** *duration*
sets recording time in seconds or frames. Frames (sectors) are indicated by a 'f' suffix (like 75f for 75 sectors). **0** sets the time for whole track.

The default is to extract the whole track.

−**E** *endianess*

−**output−endianess** *endianess*
sets endianess of the output samples to 'little', 'big' or 'machine' to override the default which is 'network byte order' (big endian). The value 'machine' or 'host' is evaluated as the actual byte order of the host CPU in the current OS.

−**F**

−**find−extremes**
finds extreme amplitudes in samples.

−**G**

−**find−mono**
finds if input samples are in mono.

−**g**

−**gui** formats the output to be better parsable by gui frontends.

−**H**

−**no−infofile**
does not write an info file, a cddb file and no cdtext file.

−**i** *index*

−**index** *index*
selects the start index.

−**J**

−**info−only**
does not write to a file, it just gives information about the disc.

−**M**

−**md5** enables calculation of MD-5 checksum for all audio bytes from the beginning of a track. The audio header is skipped when calculating the MD-5 checksum to allow to compare MD-5 sums even for files with different header type.

−**m**

−**mono** sets to mono recording.

−**no−hidden−track**
Ignore hidden tracks on the CD. By default, **cdda2wav** checks whether there might be a hidden track before track 1. This check may take a few seconds and thus can be disabled with −**no−hidden−track**.

−**N**

−**no−write**
does not write to a file, it just reads (e.g. for debugging purposes). If this option is used together with the −**e** option, the CD is read and the audio content is played back to the sound device without creating output files with audio data.

−**no−textdefaults**

By default, **cdda2wav** replaces empty CD-Text fields from tracks by the related CD-Text fiel for the whole CD in case this is defined. If the option −**no−textdefaults** is used, **cdda2wav** leaves the track related CD-Text fields empty in such a case.

−**no−textfile**
If **cdda2wav** encounters useful CD-Text information on the CD, it writes a .cdtext file. The option −**no−textfile** allows to suppress the creation of the .cdtext file.

−**o** *offset*

−**offset** *offset*
starts *offset* sectors behind start track (one sector equivalents 1/75 seconds).

−**O** *audiotype*

−**output−format** *audiotype*
can be *wav* (for wav files) or *aiff* (for apple/sgi aiff files) or *aifc* (for apple/sgi aifc files) or *au* or *sun* (for sun .au PCM files) or *cdr* or *raw* (for headerless files to be used for cd writers).

The default output format is now **wav** for all platforms as this file format has become the most common format. Note that former versions of **cdda2wav** made an exception and by default did create **au** type files on Solaris.

−**p** *percentage*

−**playback−realtime** *percentage*
changes pitch of audio data copied to sound device.

−**P** *sectors*

−**set−overlap** *sectors*
sets the initial number of overlap *sectors* for jitter correction in non-paranoia mode. Note that overlapped reads re handled differently in paranoia mode.

The default overlap in non-paranoia mode is 1.

−**paranoia**
use the paranoia library as a filter on top of cdda2wav's routines for reading. In **paranoia** mode, the latency time for the −**interactive** mode is increased to typically 5..10 seconds. This is caused by the fact that the **paranoia** code reads anything at least twice and in between needs to take care of emptying the cache RAM of the CD-ROM drive.

If the **paranoia** mode is used, **cdda2wav** displays some quality statistics for each extracted track. The following items appear in the list:

Value	Description
rderr	Number of hard read errors
skip	Number of sectors skipped due to exhausted retries
atom	Number of intra sector jitters (frame jitters) detected
edge	Number of jitters between sectors detected
drop	Number of dropped bytes fixed
dup	Number of duplicate bytes fixed
drift	Number of drifts detected
overlap	Number of dynamic overlap size raises

−**paraopts=***list*

List is a comma separated list of suboptions passed to the paranoia library.

Option	Description
help	lists all paranoia options.
disable	disables paranoia mode. Libparanoia is still being used
no-verify	switches verify off, and static overlap on
retries=amount	set the number of maximum retries per sector
overlap=amount	set the number of sectors used for statical paranoia overlap
minoverlap=amt	set the min. number of sectors for dynamic paranoia overlap
maxoverlap=amt	set the max. number of sectors for dynamic paranoia overlap
proof	set maxoverlap=*sectors−per−request*-1,retries=200

−**q**

−**quiet** quiet operation, no screen output.

−**r** *rate*

−**rate** *rate*

sets *rate* in samples per second. Possible values are listed with the −**R** option.

−**R**

−**dump−rates**

shows a list of all sample rates and their dividers.

−**S** *speed*

−**speed** *speed*

sets the cdrom device to one of the selectable speeds for reading. For maximum extraction quality, it is recommended to use speed values of 8 or below.

The default is to extract at maximum speed.

−**s**

−**stereo** sets to stereo recording.

−**start−sector** *sector*

set an absolute start sector. This option is mutually exclusive to −**track** and −**offset**.

−**t** *track[+endtrack]*

−**track** *track[+endtrack]*

−**track** *track***+max**

−**track all**

selects the start track and optionally the end track. If −**t all** is used, all audio tracks are selected. If −**t 2+max** is used, all audio tracks starting with track 2 are selected.

−**v** *itemlist*

−**verbose−level** *itemlist*

Retrieves and prints verbose information about the CD. **Level** is a list of comma separated suboptions. Each suboption controls the type of information to be reported.

Suboption	Description
!	invert the meaning of the following string
not	invert the meaning of the following string
disable	no information is given, warnings appear however
all	all information is given
toc	show table of contents
summary	show a summary of the recording parameters
indices	determine and display index offsets
catalog	retrieve and display the media catalog number MCN
mcn	retrieve and display the media catalog number MCN
trackid	retrieve and display all Intern. Standard Recording Codes ISRC
isrc	retrieve and display all Intern. Standard Recording Codes ISRC
sectors	show the table of contents in start sector notation
titles	show the table of contents with track titles (when available)
audio-tracks	list the audio tracks and their start sectors

The default value for the verbose-level is **toc,summary,sectors,titles** .

−**w**

−**wait** waits for signal, then start recording.

−**x**

−**max** sets maximum (CD) quality.

SCSI options

dev=*device*

−**D** *device*

−**device** *device*
uses *device* as the source for CDDA reading. For example /dev/cdrom for the **cooked_ioctl** interface and Bus,ID,Lun for the **generic_scsi** interface. The *device* has to correspond with the interface setting if given (see −**I** and −**interface** option below).

If no −**I** or −**interface** option has been specified, the interface setting is derived from the device name syntax. A device name that is in the form Bus,ID,Lun or contains a colon (':') defaults to the **generic_scsi** interface.

Using the **cooked_ioctl** is not recommended as this makes **cdda2wav** mainly depend on the audio extraction quality of the operating system which is usually extremely bad. For this reason, avoid using parameters like **dev=**/dev/cdrom for the device.

The setting of the environment variable **CDDA_DEVICE** is overridden by this option.

If no **dev=** option is present, or if the **dev=** option only contains a transport specifyer but no address, **cdda2wav** tries to scan the SCSI address space for CD-ROM drives. If exactly one is found, this is used by default.

For more information, see the description of the **dev=** option from **cdrecord**(1).

debug=#

debug-scsi=#
Set the debug level for the **libscg** SCSI OS abstraction layer.

kdebug=#

kdebug-scsi=#

kd=# Set the kernel debug level for the kernel driver called by the **libscg** SCSI OS abstraction layer. This option is not supported on all platforms.

−scanbus
Scan all SCSI devices on all SCSI busses and print the inquiry strings. This option may be used to find SCSI address of the CD/DVD-Recorder on a system. The numbers printed out as labels are computed by: **bus * 100 + target**

ts=# Set the maximum transfer size for a single SCSI command to #. The syntax for the **ts=** option is the same as for cdrecord fs=# or sdd bs=#.

If no **ts=** option has been specified, **cdda2wav** defaults to a transfer size of 3 MB. If libscg gets lower values from the operating system, the value is reduced to the maximum value that is possible with the current operating system. Sometimes, it may help to further reduce the transfer size or to enhance it, but note that it may take a long time to find a better value by experimenting with the **ts=** option.

Some operating systems return wrong values for the maximum transfer size. If the transfer totally hangs or resets occur, it may be appropriate to reduce the transfer size to less than 64 kB or even less than 32 kB.

−V

−verbose−scsi
enable SCSI command logging to the console. This is mainly used for debugging.

−Q

−silent−scsi
suppress SCSI command error reports to the console. This is mainly used for guis.

OS Interface options

−A *auxdevice*

−auxdevice *auxdevice*
uses *auxdevice* as CDROM drive to allow to send the CDROMMULTISESSION ioctl on Linux although the **generic_scsi** interface is in use.

−I *interface*

−interface *interface*
specifies the *interface* to use for accessing the CDROM:

generic_scsi
for sending SCSI commands directly to the drive.

cooked_ioctl
for using the programming interface supplied by the OS kernel.

The latter is not recommended as it gives lower quality and only works on a limited number of platforms.

−**interactive**

Go into interactive mode that reads commands from **stdin** and writes the textual replies to **stderr**, or the file descriptor that has been specified by the **out−fd** option. This mode has been introduced mainly to allow cdrecord to be called by gstreamer plugins.

If **cdda2wav** was called with the option −**interactive**, it reads the TOC from the medium and then waits for command input as if it has been issued a **stop** command. If the next command is a **cont** command, then **cdda2wav** extracts the whole audio part of the medium. If the next command is a **read** command, then **cdda2wav** starts extracting from the position that was indicated by the **read** command parameter.

Command	Parameters	Description
cont		continue processing at current position
exit		exit processing
help		print command help and wait for input
quit		exit processing
read	sectors *sector number*	read sectors starting from *sector number*
read	tracks *track number*	read sectors starting from *track number*
stop		stop processing and wait for new input

out−fd=*descriptor*

Redirect informational output to the file descriptor named by **descriptor**. The parameter **descriptor** specifies a UNIX file descriptor number. By default, **cdda2wav** sends informational output to **stderr**. Redirecting the informational output to a different file descriptor helps gui's and other programs that call **cdda2wav** via pipes.

audio−fd=*descriptor*

In case that the file name for the audio data file is "-", redirect audio output to the file descriptor named by **descriptor**. The parameter **descriptor** specifies a UNIX file descriptor number. By default, **cdda2wav** sends audio data to **stdout** if the output is not directed into a file. Redirecting the audio output to a different file descriptor helps gui's and other programs that call **cdda2wav** via pipes.

−**no-fork**

Do not fork for extended buffering. If −**no-fork** is used and **cdda2wav** is used to play back audio CDs in **paranoia** mode, the playback is not always uninterrupted due to lack of buffering. On the other side, allowing **cdda2wav** to fork will increase the latency time for the −**interactive** mode.

−**e**

−**echo** copies audio data to sound device from the operating system e.g. **/dev/dsp**.

sound−device=*sounddevice*

set an alternate sound device to use for −**e**.

−**n** *sectors*

−**sectors−per−request** *sectors*

reads *sectors* per request.

−**l** *buffers*

−**buffers−in−ring** *buffers*

uses a ring buffer with *buffers* total.

ENVIRONMENT VARIABLES

Some defaults for **cdda2wav** are compiled in and depend on the **Makefile** others on the **environment variable** settings.

CDDA_DEVICE
is used to set the device name. The device naming is compatible with **cdrecord**(1).

CDDBP_SERVER
is used for cddbp title lookups when supplied.

CDDBP_PORT
is used for cddbp title lookups when supplied.

RSH If the **RSH** environment variable is present, the remote connection will not be created via **rcmd**(3) but by calling the program pointed to by **RSH**. Use e.g. **RSH=**/usr/bin/ssh to create a secure shell connection.

Note that this forces **cdda2wav** to create a pipe to the **rsh(1)** program and disallows **cdda2wav** to directly access the network socket to the remote server. This makes it impossible to set up performance parameters and slows down the connection compared to a **root** initiated **rcmd(3)** connection.

RSCSI If the **RSCSI** environment variable is present, the remote SCSI server will not be the program **/opt/schily/sbin/rscsi** but the program pointed to by **RSCSI**. Note that the remote SCSI server program name will be ignored if you log in using an account that has been created with a remote SCSI server program as login shell.

EXIT STATUS

cdda2wav uses the following exit codes to indicate various degress of success:

Exitcode	Description
0	no errors encountered, successful operation.
1	usage or syntax error. cdda2wav got inconsistent arguments.
2	permission (un)set errors. permission changes failed.
3	read errors on the cdrom/burner device encountered.
4	write errors while writing one of the output files encountered.
5	errors with soundcard handling (initialization/write).
6	errors with stat() system call on the read device (cooked ioctl).
7	pipe communication errors encountered (in forked mode).
8	signal handler installation errors encountered.
9	allocation of shared memory failed (in forked mode).
10	dynamic heap memory allocation failed.
11	errors on the audio cd medium encountered.
12	device open error in ioctl handling detected.
13	race condition in ioctl interface handling detected.
14	error in ioctl() operation encountered.
15	internal error encountered. Please report back!!!
16	error in semaphore operation encountered (install / request).
17	could not get the scsi transfer buffer.
18	could not create pipes for process communication (in forked mode).

DISCUSSION

cdda2wav is able to read parts of an **audio** CD or **multimedia** CDROM (containing audio parts) directly digitally. These parts can be written to a file, a pipe, or to a sound device.

cdda2wav stands for **CDDA** to **WAV** (where **CDDA** stands for compact disc digital audio and **WAV** is a sound sample format introduced by MS Windows). It allows copying **CDDA** audio data from the CDROM drive into a file in **WAV** or other formats.

Some versions of **cdda2wav** may try to get higher real-time scheduling priorities to ensure smooth (uninterrupted) operation. These priorities are available for super users and are higher than those of 'normal' processes. Thus delays are minimized.

If you only have one CDROM and it is loaded with an audio CD, you may simply invoke **cdda2wav** and it will create the sound file **audio.wav** recording the whole track beginning with track 1 in stereo at 16 bit at 44100 Hz sample rate, if your file system has enough space free. Otherwise recording time will be limited. For details see files **README** and **README.INSTALL**.

If you have more then one CD-ROM type drive in the system, you need to specify the **dev=** option.

HINTS ON OPTIONS

Most of the options are used to control the format of the WAV file. In the following text most of them are discussed in a more verbose way.

Select Device

dev=*device* selects the CDROM drive device to be used. The specifier given should correspond to the selected interface (see below). For the **cooked_ioctl** interface this is the cdrom device descriptor. **The SCSI devices used with the generic SCSI interface however are addressed with their SCSI-Bus, SCSI-Id, and SCSI-Lun instead of the generic SCSI device descriptor.** One example for a SCSI CDROM drive on bus 0 with SCSI ID 3 and lun 0 is **dev=0,3,0**.

Select Auxiliary device

−A *auxdevice* may be needed in some rare cases for CD-Extra handling. **Cdda2wav** usually has no problem to get the multi-session information for CD-Extra using raw SCSI commands. For Non-SCSI-CDROM drives this is the same device as given by **dev=** (see above). For SCSI-CDROM drives it is the CDROM drive (SCSI) device (i.e. **/dev/sr0**) corresponding to the SCSI device (i.e. **0,3,0**). It has to match the device used for sampling.

Select Interface

−I *interface* selects the CDROM drive communication method. This interface method is typically automatically selected from the device name. For SCSI drives **generic_scsi** is used (cooked_ioctl may not be available for all devices). Valid names are **generic_scsi** and **cooked_ioctl**. The first uses the generic SCSI interface, the latter uses the ioctl of the CDROM driver. The latter variant works only when the kernel driver supports **CDDA** reading. This entry has to match the selected CDROM device (see above).

Enable echo to soundcard

−e copies audio data to the sound card while recording, so you hear it nearly simultaneously. The soundcard gets the same data that is recorded. This is time critical, so it works best with the **−q** option. To use **cdda2wav** as a pseudo CD player without recording in a file you could use

cdda2wav −q −e −t2 −d0 −N

to play the whole second track or

cdda2wav −q −e −B −N

to play the whole disk. This feature reduces the recording speed to at most onefold speed.

Change pitch of echoed audio

−p percentage changes the pitch of all audio echoed to a sound card. Only the copy to the soundcard is affected, the recorded audio samples in a file remain the same. Normal pitch, which is the default, is given by 100%. Lower percentages correspond to lower pitches, i.e. −p 50 transposes the audio output one octave lower. See also the script **pitchplay** as an example. This option was contributed by Raul Sobon.

Select mono or stereo recording

−m or **−c 1** selects mono recording (both stereo channels are mixed), **−s** or **−c 2** or **−c s** selects stereo recording. Parameter s will swap both sound channels.

Select maximum quality

−x will set stereo, 16 bits per sample at 44.1 KHz (full CD quality). Note that other format options given later can change this setting.

Select sample quality

−**b 8** specifies 8 bit (1 Byte) for each sample in each channel; −**b 12** specifies 12 bit (2 Byte) for each sample in each channel; −**b 16** specifies 16 bit (2 Byte) for each sample in each channel (Ensure that your sample player or sound card is capable of playing 12-bit or 16-bit samples). Selecting 12 or 16 bits doubles file size. 12-bit samples are aligned to 16-bit samples, so they waste some disk space.

Select sample rate

−**r** *samplerate* selects a sample rate. *samplerate* can be in a range between 44100 and 900. Option −**R** lists all available rates.

Select sample rate divider

−**a** *divider* selects a sample rate divider. *divider* can be minimally 1 and maximally 50.5 and everything between in steps of 0.5. Option −**R** lists all available rates.

To make the sound smoother at lower sampling rates, **cdda2wav** sums over *n* samples (where *n* is the specific dividend). So for 22050 Hertz output we have to sum over 2 samples, for 900 Hertz we have to sum over 49 samples. This cancels higher frequencies. Standard sector size of an audio CD (ignoring additional information) is 2352 Bytes. In order to finish summing for an output sample at sector boundaries the rates above have to be chosen. Arbitrary sampling rates in high quality would require some interpolation scheme, which needs much more sophisticated programming.

List a table of all sampling rates

−**R** shows a list of all sample rates and their dividers. Dividers can range from 1 to 50.5 in steps of 0.5.

Select start track and optionally end track

−**t** *n*+*m* selects **n** as the start track and optionally **m** as the last track of a range to be recorded. These tracks must be from the table of contents. This sets the track where recording begins. Recording can advance through the following tracks as well (limited by the optional end track or otherwise depending on recording time). Whether one file or different files are then created depends on the −**B** option (see below).

Select start index

−**i** *n* selects the index to start recording with. Indices other than 1 will invoke the index scanner, which will take some time to find the correct start position. An offset may be given additionally (see below).

Set recording duration

−**d n** sets recording time to *n* seconds or set recording time for whole track if *n* is zero. In order to specify the duration in frames (sectors) also, the argument can have an appended 'f'. Then the numerical argument is to be taken as frames (sectors) rather than seconds. Please note that if track ranges are being used they define the recording time as well thus overriding any −**d** option specified times.

Recording time is defined as the time the generated sample will play (at the defined sample rate). Since it's related to the amount of generated samples, it's not the time of the sampling process itself (which can be less or more). It's neither strictly coupled with the time information on the audio CD (shown by your hifi CD player). Differences can occur by the usage of the −**o** option (see below). Notice that recording time will be shortened, unless enough disk space exists. Recording can be aborted at anytime by pressing the break character (signal SIGQUIT).

Record all tracks of a complete audio CD in separate files

−**B** copies each track into a separate file. A base name can be given. File names have an appended track number and an extension corresponding to the audio format. To record all audio tracks of a CD, use a sufficient high duration (i.e. −d99999).

Set start sector offset

−**o** *sectors* increments start sector of the track by *sectors*. By this option you are able to skip a certain amount at the beginning of a track so you can pick exactly the part you want. Each sector runs for 1/75 seconds, so you have very fine control. If your offset is so high that it would not fit into the current track, a warning message is issued and the offset is ignored. Recording time is not reduced. (To skip

introductory quiet passages automagically, use the **−w** option see below.)

Wait for signal option

−w Turning on this option will suppress all silent output at startup, reducing possibly file size. **cdda2wav** will watch for any signal in the output signal and switches on writing to file.

Find extreme samples

−F Turning on this option will display the most negative and the most positive sample value found during recording for both channels. This can be useful for readjusting the volume. The values shown are not reset at track boundaries, they cover the complete sampling process. They are taken from the original samples and have the same format (i.e. they are independent of the selected output format).

Find if input samples are in mono

−G If this option is given, input samples for both channels will be compared. At the end of the program the result is printed. Differences in the channels indicate stereo, otherwise when both channels are equal it will indicate mono.

Undo the pre-emphasis in the input samples

−T Some older audio CDs are recorded with a modified frequency response called pre-emphasis. This is found mostly in classical recordings. The correction can be seen in the flags of the Table Of Contents often. But there are recordings, that show this setting only in the subchannels. If this option is given, the index scanner will be started, which reads the q-subchannel of each track. If pre-emphasis is indicated in the q-subchannel of a track, but not in the TOC, pre-emphasis will be assumed to be present, and subsequently a reverse filtering is done for this track before the samples are written into the audio file.

Set audio format

−O audiotype can be *wav* (for wav files) or *au* or *sun* (for sun PCM files) or *cdr* or *raw* (for headerless files to be used for cd writers). All file samples are coded in linear pulse code modulation (as done in the audio compact disc format). This holds for all audio formats. Wav files are compatible to Wind∗ws sound files, they have lsb,msb byte order which is the opposite byte order to the one used on the audio cd. The default filename extension is '.wav'. Sun type files are not like the older common logarithmically coded .au files, but instead as mentioned above linear PCM is used. The byte order is msb,lsb to be compatible. The default filename extension is '.au'. The AIFF and the newer variant AIFC from the Apple/SGI world store their samples in bigendian format (msb,lsb). In AIFC no compression is used. Finally the easiest 'format', the cdr aka raw format. It is done per default in msb,lsb byte order to satisfy the order wanted by most cd writers. Since there is no header information in this format, the sample parameters can only be identified by playing the samples on a soundcard or similar. The default filename extension is '.cdr' or '.raw'.

Select cdrom drive reading speed

−S speed allows to switch the cdrom drive to a certain level of speed in order to reduce read errors. The argument is transferred verbatim to the drive. Details depend very much on the cdrom drives. An argument of 0 for example is often the default speed of the drive, a value of 1 often selects single speed.

Enable MD5 checksums

−M count enables calculation of MD-5 checksum for 'count' bytes from the beginning of a track. This was introduced for quick comparisons of tracks.

Use Monty's libparanoia for reading of sectors

−paranoia selects an alternate way of extracting audio sectors. Monty's library is used with the following default options:

PARANOIA_MODE_FULL, but without PARANOIA_MODE_NEVERSKIP

for details see Monty's libparanoia documentation. In this case the option **−P** has no effect.

Do linear or overlapping reading of sectors

(This applies unless option **−paranoia** is used.) **−P sectors** sets the given number of sectors for initial overlap sampling for jitter correction. Two cases are to be distinguished. For nonzero values, some

sectors are read twice to enable cdda2wav's jitter correction. If an argument of zero is given, no overlap sampling will be used. For nonzero overlap sectors cdda2wav dynamically adjusts the setting during sampling (like cdparanoia does). If no match can be found, cdda2wav retries the read with an increased overlap. If the amount of jitter is lower than the current overlapped samples, cdda2wav reduces the overlap setting, resulting in a higher reading speed. The argument given has to be lower than the total number of sectors per request (see option *-n* below). Cdda2wav will check this setting and issues a error message otherwise. The case of zero sectors is nice on low load situations or errorfree (perfect) cdrom drives and perfect (not scratched) audio cds.

Set the transfer size

−n sectors will set the transfer size to the specified sectors per request.

Set number of ring buffer elements

−l buffers will allocate the specified number of ring buffer elements.

Set endianess of input samples

−C endianess will override the default settings of the input format. Endianess can be set explicitly to "little", "big" or "machine" or to the automatic endianess detection based on voting with "guess".

Set endianess of output samples

−E endianess (endianess can be "little", "big" or "machine") will override the default settings of the output format.

Verbose option

−v itemlist prints more information. A list allows selection of different information items.

help	Print a summary of possible members of the diffopts list.
!	Invert the meaning of the following string. No comma is needed after the exclamation mark.
not	Invert the meaning of all members in the diffopts list i.e. exclude all present options from an initially complete set compare list. When using **csh**(1) you might have problems to use **!** due to its strange parser. This is why the **not** alias exists.
disable	disables verbosity
all	all information is given
toc	displays the table of contents
summary	displays a summary of recording parameters
indices	invokes the index scanner and displays start positions of indices
catalog	retrieves and displays a media catalog number
trackid	retrieves and displays international standard recording codes
sectors	displays track start positions in absolute sector notation

To combine several requests just list the suboptions separated with commas.

The table of contents

The display will show the table of contents with number of tracks and total time (displayed in *mm*:*ss*.*hh* format, *mm*=minutes, *ss*=seconds, *hh*=rounded 1/100 seconds). The following list displays track number and track time for each entry. The summary gives a line per track describing the type of the track.

track preemphasis copypermitted tracktype chans

The **track** column holds the track number. **preemphasis** shows if that track has been given a non linear frequency response. NOTE: You can undo this effect with the **−T** option. **copy−permitted** indicates if this track is allowed to copy. **tracktype** can be data or audio. On multimedia CDs (except hidden track CDs) both of them should be present. **channels** is defined for audio tracks only. There can be two or

four channels.

No file output

−N this debugging option switches off writing to a file.

No infofile generation

−H this option switches off creation of an info file and a cddb file.

Generation of simple output for gui frontends

−g this option switches on simple line formatting, which is needed to support gui frontends (like xcdroast).

Verbose SCSI logging

−V this option switches on logging of SCSI commands. This will produce a lot of output (when SCSI devices are being used). This is needed for debugging purposes. The format is the same as being used with the cdrecord program, see **cdrecord**(1) for more information.

Quiet option

−q suppresses all screen output except error messages. That reduces cpu time resources.

Just show information option

−J does not write a file, it only prints information about the disc (depending on the **−v** option). This is just for information purposes.

CDDBP support

Lookup album and track titles option

−L cddbp mode Cdda2wav tries to retrieve performer, album-, and track titles from a cddbp server. The default server right now is 'freedb.freedb.org'. It is planned to have more control over the server handling later. The parameter defines how multiple entries are handled:

0 interactive mode, the user chooses one of the entries.

1 take the first entry without asking.

Set server for title lookups

cddbp−server servername When using −L or −cddb, the server being contacted can be set with this option.

Set portnumber for title lookups

cddbp−port portnumber When using −L or −cddb, the server port being contacted can be set with this option.

HINTS ON USAGE

Don't create samples you cannot read. First check your sample player software and sound card hardware. I experienced problems with very low sample rates (stereo <= 1575 Hz, mono <= 3675 Hz) when trying to play them with standard WAV players for sound blaster (maybe they are not legal in **WAV** format). Most CD-Writers insist on audio samples in a bigendian format. Now cdda2wav supports the **−E endianess** option to control the endianess of the written samples.

If your hardware is fast enough to run cdda2wav uninterrupted and your CD drive is one of the 'perfect' ones, you will gain speed when switching all overlap sampling off with the **−P 0** option. Further fine tuning can be done with the **−n sectors** option. You can specify how much sectors should be requested in one go.

Cdda2wav supports **pipes**. Use a filename of − to let cdda2wav output its samples to standard output.

Conversion to other sound formats can be done using the **sox** program package (although the use of **sox −x** to change the byte order of samples should be no more necessary; see option **−E** to change the output byteorder).

If you want to sample more than one track into different files in one run, this is currently possible with the **−B** option. When recording time exceeds the track limit a new file will be opened for the next track.

FILES

Cdda2wav can generate a lot of files for various purposes.

Audio files:

There are audio files containing samples with default extensions .wav, .au, .aifc, .aiff, and .cdr according to the selected sound format. These files are not generated when option (**−N**) is given. Multiple files may be written when the bulk copy option (**−B**) is used. Individual file names can be given as arguments. If the number of file names given is sufficient to cover all included audio tracks, the file names will be used verbatim. Otherwise, if there are less file names than files needed to write the included tracks, the part of the file name before the extension is extended with '_dd' where dd represents the current track number.

Cddb and Cdindex files:

If cdda2wav detects cd-extra or cd-text (album/track) title information, then .cddb, .cdindex and .cdtext files are generated unless suppressed by the option **−H**. They contain suitable formatted entries for submission to audio cd track title databases in the internet. The CDINDEX and CDDB(tm) systems are currently supported. For more information please visit www.musicbrainz.org and www.freedb.com.

Inf files:

The inf files are describing the sample files and the part from the audio cd, it was taken from. They are a means to transfer information to a cd burning program like cdrecord. For example, if the original audio cd had pre-emphasis enabled, and cdda2wav **−T** did remove the pre-emphasis, then the inf file has pre-emphasis not set (since the audio file does not have it anymore), while the .cddb and the .cdindex have pre-emphasis set as the original does.

WARNING

IMPORTANT: it is prohibited to sell copies of copyrighted material by noncopyright holders. This program may not be used to circumvent copyrights. The user acknowledges this constraint when using the software.

BUGS

The index scanner may give timeouts.

The resampling (rate conversion code) uses polynomial interpolation, which is not optimal.

Cdda2wav should use threads.

Cdda2wav currently cannot sample hidden audio tracks that reside in track #1 index 0.

ACKNOWLEDGEMENTS

Thanks goto Project MODE (http://www.mode.net/) and Fraunhofer Institut für integrierte Schaltungen (FhG-IIS) (http://www.iis.fhg.de/) for financial support. Plextor Europe and Ricoh Japan provided cdrom disk drives and cd burners which helped a lot to develop this software. Rammi has helped a lot with the debugging and showed a lot of stamina when hearing 100 times the first 16 seconds of the first track of the Krupps CD. Libparanoia contributed by Monty (Christopher Montgomery) xiphmont@mit.edu.

AUTHOR

Heiko Eissfeldt heiko@colossus.escape.de (1993-2004)

2004-today:

Jörg Schilling
Seestr. 110
D-13353 Berlin
Germany

DATE

12 Jan 2010

INTERFACE STABILITY

The interfaces provided by **cdda2wav** are designed for long term stability. As **cdda2wav** depends on interfaces provided by the underlying operating system, the stability of the interfaces offered by **cdda2wav** depends on the interface stability of the OS interfaces. Modified interfaces in the OS may enforce modified interfaces in **cdda2wav**.